



multisensoryroom



MiLEroom



sensorypool



soft play



sensory bathroom



interactive floor & walls

M Clayton
26/09/2017
V1
010033

PREPARED
DATE
VER NO.
PRODUCT CODE

Instruction Manual

For

IRiS LED Fibre Optic Lightsource



experia
multisensory for everyone

Experia
Acorn Phase 3, High Street
Barnsley, South Yorkshire
S72 7BD, United Kingdom

T 0800 612 6077
Einfo@experia-innovations.co.uk
Wwww.experia-innovations.co.uk

Instruction Manual

Congratulations on the purchase of your IRiS LED Fibre Optic Lightsource!

The IRiS LED Fibre Optic Lightsource has been designed specifically for people with special needs and should, if used in accordance with these guidelines, offer years of switching learning and fun!

The IRiS LED Fibre Optic Lightsource offers endless opportunities to develop numerous skills including colour recognition, cause and effect, and many more. It transforms fibre optics and gives old tired optics a new lease of life.

The IRiS LED Fibre Optic Lightsource is an IRiS Listener and can be controlled by any number of IRiS Talkers.

Please ensure you read this Instruction Manual in full before operating the unit.

Heed all warnings on the product and within this manual. If upon receipt of this product, the user suspects that the product is defective, and/or requires service or repair due to malfunction or damage to the product, please contact the manufacturer immediately. Please be aware that improper installation and/or use or misuse of this product may result in injury, death, or adverse reactions to its user. This product is intended to be installed and/or use by a trained professional. Failure to comply with these precautions or with specific warnings elsewhere in this manual violates safety standards of design, manufacture, and intended uses of the product.

Features

- IRiS Wirefree Compatible
- Stylish Design
- Completely Silent
- Cool Running
- LED Driven so no lamp change
- Bright LED
- Standard 30mm Optic Termination Socket
- Low Voltage
- Easy to use
- 3 Year Manufacturers Guarantee (Return to base)

Instruction Manual

Getting Started

1. Connect the fibre optics to the front of the unit and tighten the securing screw.
2. Connect the XLR connector on the transformer supplied into the socket on the back of the unit.
3. Connect the standard plug to a mains outlet.
4. The unit will now illuminate and scroll through the standard IRiS colours before going out.
5. Now it's ready to use.
6. Decide which Talker you want to control the LED Fibre Optic Lightsource with then go to the Pairing section.

Pairing to IRiS Talkers

This procedure is split into 2 sections, one for those who do not have an IRiS Master Pairer and for those who do.

Without an IRiS Master Pairer

Every IRiS Listener has a button on it called a pairing button. To get the IRiS LED Fibre Optic Lightsource to work with a product, first turn on the IRiS LED Fibre Optic Lightsource then decide which IRiS Talker you want to control it with – in this example we use the IRiS Qube but all work in the same manner.

Next find the pairing button on the back of the unit and press it. You then need to activate the IRiS Qube within 5 seconds (in this case you would turn the Qube over). The IRiS LED Fibre Optic Lightsource will now change colour every time you turn the Qube if correctly paired, if it does not then repeat the above.

With an IRiS Master Pairer

To get the IRiS LED Fibre Optic Lightsource to work with a product, first turn on the IRiS LED Fibre Optic Lightsource then decide which IRiS Talker you want to control it with – in this example we use the IRiS Qube but all work in the same manner. Then find the button on the IRiS Master Pairer that corresponds with your product and press it. You then need to activate the IRiS Qube within 5 seconds (in this case you would turn the Qube over). The IRiS LED Fibre Optic Lightsource will now change colour every time you turn the Qube if correctly paired, if it does not then repeat the above.

Instruction Manual

Cleaning and Maintenance

The unit should be cleaned with a damp soft cloth. A non-abrasive cleaning agent may be used for stubborn stains. Ensure no liquid enters the unit.

The unit has been designed for use by people with special needs however this does NOT mean it is unbreakable.

Lamp Change

Not required! It uses an LED which lasts for years!

Troubleshooting

Q. The unit doesn't work.

A1. Is it switched on? If so, see A2

A2. Has the unit scrolled through its colours? If so, see A3

A3. Has the unit been paired to an IRiS Talker? if so, see A4

A4. Is the battery in the IRiS Talker fully charged? If so, see A5

A5. Have you tried a different IRiS Talker? If so, please contact us.

Instruction Manual

Contact Details

For USA please email office@experia-usa.com

For Ireland please email support@experia-ireland.ie

For UK and rest of the world email support@experia-innovations.co.uk

Telephone: +44 (0) 845 644 0977.

Please note: email is our support teams preferred communication and this takes precedence over telephone calls.

QUESTIONS & IDEAS?

If you have an idea on how to improve this product or want to see your product idea realised, please email: ideas@experia-innovations.co.uk.

All ideas are presented to our OT, technical and finance department and if all procedures are passed we will contact you to discuss your idea further.

We can't promise to develop every product but if it's a great idea, we'll try!

Manufactured proudly in the UK by:

Experia, Acorn Phase 3, High Street, Grimethorpe, S72 7BD.



© Copyright 2017 Experia All rights reserved. Experia is a registered trademark