

M Clayton
11/02/2020
V1
010061

PREPARED
DATE
VER NO.
PRODUCT CODE



Installation Manual

For

IRiS LED Fibre Optic Wall Cascade

experia
multisensory for everyone

Experia
Acorn Phase 3, High Street
Barnsley, South Yorkshire
S72 7BD, United Kingdom

T 0800 612 6077
Einfo@experia-innovations.co.uk
Wwww.experia-innovations.co.uk

Installation Manual

EXPERIA GENERAL WARNINGS AND CAUTIONS

PLEASE READ THE INSTRUCTIONS WITHIN THIS MANUAL CAREFULLY BEFORE INSTALLING OR OPERATING THIS PRODUCT. Heed all warnings on the product and within this manual. If upon receipt of this product, the user suspects that the product is defective, and/or requires service or repair due to malfunction or damage to the product, please contact the manufacturer immediately. Please be aware that improper installation and/or use or misuse of this product may result in injury, death, or adverse reactions to its user. This product is intended to be installed and/or use by a trained professional. Failure to comply with these precautions or with specific warnings elsewhere in this manual violates safety standards of design, manufacture, and intended uses of the product.

The IRIS LED Fibre Optic Cascade is a heavy product and MUST be fitted by a trained professional. It is recommended that the unit be fitted to a solid wall, ie brick. If fitting to a plasterboard wall, the fixing MUST be located to the stud-work. The unit is not supplied with wall fixings, as these must be provided by the installer, to suit the wall the product is to be fitted to.

Tools Required

1. Ladders
2. Drill
3. Hammer
4. 17mm spanner
5. Spirit level
6. Pencil
7. Suitable fixings and hardware for wall construction

Installation Manual

Mounting the LED Fibre Optic Cascade to the wall

When choosing the location of a wall bracket, always take into consideration hidden services like pipes or electrical cable. If unsure use a detection device. Also the Cascade wants to be high enough so it will not be an obstruction for people walking under it.

1. Choose the location of the product
2. Remove the two bolts, and nylon washers that hold the wall plate from the cascade.
3. Hold the wall plate in place, and using the spirit level ensuring it is straight, and mark the six mounting holes.
4. Refer to your chosen fixings instruction guide and secure the wall plate to the wall.
5. Ensure all 6 fixings are secure and the wall plate is tight to the wall.
6. With the help of an assistant, offer the cascade up to the wall plate, Ensure a nylon washer is between the metal parts of the bracket. Refit the two bolt in the top and bottom of the bracket assembly.
7. Using the spanner, tighten the bolts, until the cascade take a firm push to pivot on the bracket.
8. Take the supplied transformer, and connect it to a suitable mains supply via the mains plug.
9. Connect the transformer to the light source located inside the cascade.
10. Turn on the mains supply and the fibre optic should illuminate.
11. Please refer to the instruction manual for daily use of the item.

We recommend that a maintenance procedure is put into place to periodically check the secure fixing of the product and wall bracket.

Installation Manual

Contact Details

For USA please email

For Canada please email support@experia-canada.com

For UK and rest of the world email support@experia-innovations.co.uk

Telephone: 0044 (0) 845 644 0977.

Please note: email is our support teams preferred communication and this takes precedence over telephone calls.

QUESTIONS & IDEAS?

If you have an idea on how to improve this product or want to see your product idea realised, please email: ideas@experia-innovations.co.uk.

All ideas are presented to our OT, technical and finance department and if all procedures are passed we will contact you to discuss your idea further.

We can't promise to develop every product but if it's a great idea, we'll try!

Manufactured proudly in the UK by:

Experia, Acorn Phase 3, High Street, Grimethorpe, S72 7BD.



© Copyright 2017 Experia All rights reserved. Experia is a registered trademark